


8 pin mini-DIN ACC Socket

Female is on the radio


- 1 13.8V (unswitched)
- 2 Tx O/C to gnd
- 3 Gnd
- 4 TxData
- 5 RxData
- 6 Band Data (analog manual P80)
- 7 ALC
- 8 Tx Inh

Shield -

8 pin mini-DIN



male




female


Mouse or Keyboard Cable 6 pin mini-DIN

- | | |
|-------|------------------|
| 1 N/C | Data in |
| 2 Or | Gnd |
| 3 Blu | PTT |
| 4 Grn | Data out |
| 5 N/C | Data out 1200bps |
| 6 Wht | SQL - Tx Inh |

Shield Blk



male



female

CAT cable serial I/F for FT817 ACC 8 pin mini-DIN connector

Function 8 pin mini-Din Color

- | | |
|---------|-------|
| TxDData | 4 Or |
| RxDData | 5 Blu |
| Gnd | 3 Blk |

Notes

- 1 Data levels are TTL 5V
- 2 The Baud rate must be set manually on this transceiver see manual p58 menu item 14